

ED300

Smoke and Heat detector

The ED300 smoke and heat detector has new smoke and temperature sensing technologies. As a result, this improved reliability detector responds well to all types of fires (especially to fast burning blazing fires involving inflammable liquids, which produce a limited amount of smoke) and is highly immune to false alarms.

The ED300 can be set to the sensitivity mode which best suits the application:



- Plus Mode (set at factory): the detector will trigger an alarm when the measured values exceed the set smoke threshold (configurable as per the ED100), or when the measured values exceed the set heat threshold (configurable as per the ED200). Furthermore, in the event of a rise in temperature, the smoke detection sensitivity will be taken to the maximum value. This operating mode, characterized by high sensitivity allows detection of fast burning blazing fires (for example, fires involving inflammable liquids such as alcohol)
 - OR Mode: the detector will trigger an alarm when the measured values exceed the set smoke threshold (configurable as per the ED100), or when the measured values exceed the set heat threshold (configurable as per the ED200). This operating mode, characterized by discrete sensitivity analysis, allows the detector to sense fires with a high emission of smoke and low heat output (for example, smouldering fires) and also fires with low emission of smoke and high heat output (for example, burning chemicals)
- AND Mode: the detector will trigger an alarm only when the set smoke and heat thresholds (configurable as per the ED100 and ED200) are exceeded at the same time. Given the reduced response, it is necessary to evaluate the risk factor before selecting this operating mode
- SMOKE Mode: the detector will operate as per the ED100
- HEAT Mode: the detector will operate as per the ED200

ENE series detectors, as a result of advanced technologies based on new-generation microprocessors, represent the most advanced technology that fire detection equipment can offer today.

They provide a vast spectrum of options and flexible functions, all configurable from the control panel (Versa++ technology). ENE series detectors are capable of implementing a sophisticated set of algorithms, custom created by Inim's R&D professionals, which ensure unequalled reliability and the highest immunity to false alarms.

Thanks to INIM's leading-edge LoopMap technology, you can now connect to the control panel by means of a computer or EDRV1000 driver and reconstruct the exact installation topology and obtain an easy-to-use, interactive loop layout map which greatly simplifies and speeds up searches relating to faults and maintenance work.

These detectors have passed - with flying colours - all the tests taken at the LPCB test facility, the prestigious English certification service. And, thus hold the right to use this mark in addition to the obligatory CPD certification for the commercialization of fire detectors.

Parameter	ED100	ED200	ED300
Operating voltage	19-30 Vdc		
Consumption during standby	200 uA		
Consumption during alarm	Max 10 mA		
Sensitivity	0.08 - 0.10 - 0.12 - 0.15 dB/m	A1R (58°C + RoR) - B (72°C) - BR(72°C + RoR) - A2S (58°C)	0.08 - 0.10 - 0.12 - 0.15 dB/m ----- A1R (58°C + RoR) - B (72°C) - BR(72°C + RoR) - A2S (58°C) ----- AND -OR - PLUS Mode
Operating temperature	-5°C + 40°C		
Height including base	46mm		54mm
Diameter	110mm		
Weight (with base)	160g		
Weight (without base)	90g		